

The Capstone-RISC-V Instruction Set Reference

Table of Contents

1. Introduction	4
1.1. Goals	4
1.2. Major Design Elements	4
1.3. Capstone-RISC-V ISA Overview	5
1.4. Assembly Mnemonics	5
1.5. Notations	5
1.6. Bibliography	6
2. Programming Model	7
2.1. Capabilities	7
2.2. Extension to General-Purpose Registers	9
2.3. Extension to Other Registers	10
2.4. Added Registers	10
2.5. Extension to Memory	10
2.6. Instruction Set	10
3. Capability Manipulation Instructions	12
3.1. Cursor, Bounds, and Permissions Manipulation	12
3.2. Type Manipulation	14
3.3. Dropping	16
3.4. Revocation	16
4. Memory Access Instructions	18
4.1. Load/Store with Capabilities	18
4.2. Load/Store Capabilities	18
5. Control Flow Instructions	19
5.1. Jump to Capabilities	19
5.2. Domain Crossing	19
5.3. World Switching	21
6. Adjustments to Existing Instructions	22
7. Interrupts and Exceptions	23
8. Memory Consistency Model	24
Appendix A: Debugging Instructions (Non-Normative)	25
Appendix B: Instruction Listing	26
Appendix C: Assembly Code Examples	29
Appendix D: Abstract Binary Interface (Non-Normative)	30

Contributors to this document include (in alphabetical order): Jason Zhijingcheng Yu

Version Information: Draft version. Refer to the commit hash.

1. Introduction

The Capstone project is an effort to explore the design of a new CPU instruction set architecture that achieves multiple security goals including memory safety and isolation with one unified hardware abstraction.

1.1. Goals

The ultimate goal of Capstone is to unify the numerous hardware abstracts that have been added as extensions to existing architectures as afterthought mitigations to security vulnerabilities. This goal requires a high level of flexibility and extensibility of the Capstone architecture. More specifically, we aim to support the following in a unified manner.

Exclusive access

Software should be guaranteed exclusive access to certain memory regions if needed. This is in spite of the existence of software traditionally entitled to higher privileges such as the OS kernel and the hypervisor.

Revocable delegation

Software components should be able to delegate authority to other components in a revocable manner. For example, after an untrusted library function has been granted access to a memory region, the caller should be able to revoke this access.

Dynamically extensible hierarchy

The hierarchy of authority should be dynamically extensible, unlike traditional platforms which follow a static hierarchy of hypervisor-kernel-user. This makes it possible to use the same set of abstractions for memory isolation and memory sharing regardless of where a software component lies in the hierarchy.

Safe context switching

A mechanism of context switching without trusting any other software component should be provided. This allows for a minimal TCB if necessary in case of a highly security-critical application.

1.2. Major Design Elements

The Capstone architecture design is based on the idea of capabilities, which are unforgeable tokens that represent authority to perform memory accesses and control flow transfers. Capstone extends the traditional capability model with new capability types including the following.

Linear capabilities

Linear capabilities are guaranteed not to alias with other capabilities. Operations on linear capabilities maintain this property. For example, linear capabilities cannot be duplicated. Instead, they can only be moved around across different registers or between registers and memory. They can hence enable safe exclusive access to memory regions. Capabilities that do not have this property are called *non-linear* capabilities.

Revocation capabilities

Revocation capabilities cannot be used to perform memory accesses or control flow transfers. Instead, they convey the authority to revoke other capabilities. Each revocation capability is derived from a linear capability and can later be used to revoke (i.e., invalidate) capability derived from the same linear capability. This mechanism enables revocable and arbitrarily extensible chains of delegation of authority.

Uninitialised capabilities

Uninitialised capabilities convey write-only authority to memory. They can be turned into linear capabilities after the memory region has been "initialised", that is, when the whole memory region has been overwritten with fresh data. Uninitialised capabilities enable safe initialisation of memory regions and prevent secret leakage without incurring extra performance overhead.

1.3. Capstone-RISC-V ISA Overview

While Capstone does not assume any specific modern ISA, we choose to propose a Capstone extension to RISC-V due to its open nature and the availability of toolchains and simulators.

The Capstone-RISC-V ISA is a 64-bit RISC-V extension that makes the following types of changes to the base architecture:

- Each general-purpose register is extended to 129 bits to accomodate 128-bit capabilities.
- New instructions for manipulating capabilities are added.
- New instructions for memory accesses using capabilities are added.
- New instructions for control flow transfers using capabilities are added.
- Semantics of a small number of existing instructions are changed to support capabilities.
- Semantics of interrupts and exceptions are changed to support capabilities.

1.4. Assembly Mnemonics

Each Capstone-RISC-V instruction is given a mnemonic prefixed with **CS.**. In contexts where it is clear we are discussing Capstone-RISC-V instructions, we will omit the **CS.** prefix for brevity.

In assembly code, the list of operands to an instruction is supplied following the instruction mnemonic, with the operands separated by commas, in the order of **rd**, **rs1**, **rs2**, **imm** for any operand the instruction expects.

1.5. Notations

When specifying the semantics of instructions, we use the following notations to represent the type of each operand:

I

Integer register.

C

Capability register.

S

Sign-extended immediate.

Z

Zero-extended immediate.

1.6. Bibliography

The initial design of Capstone has been discussed in the following paper:

- [Capstone: A Capability-based Foundation for Trustless Secure Memory Access](#) by Jason Zhijingcheng Yu, Conrad Watt, Aditya Badole, Trevor E. Carlson, Prateek Saxena. In *Proceedings of the 32nd USENIX Security Symposium*. Annaheim, CA, USA. August 2023.

2. Programming Model

The Capstone-RISC-V ISA has extended the part of the machine state, including both some registers and the memory, to enable the storage and handling of capabilities.

2.1. Capabilities

2.1.1. Width

The width of a capability is 128 bits. We represent this as $CLEN = 128$. Note that this does not affect the width of a raw address, which is $XLEN = 64$ bits.

2.1.2. Fields

Each capability has the following architecturally-visible fields:

Table 1. Fields in a capability

Name	Range	Description
valid	$0..1$	Whether the capability is valid: 0 = invalid, 1 = valid
type	$0..5$	The type of the capability: 0 = linear, 1 = non-linear, 2 = revocation, 3 = uninitialised, 4 = sealed, 5 = sealed-return
cursor	$0..2^{XLEN}-1$	Not applicable when $type = 4$ (sealed) or $type = 5$ (sealed-return). The memory address the capability points to (to be used for the next memory access)
base	$0..2^{XLEN}-1$	The base memory address of the memory region associated with the capability
end	$0..2^{XLEN}-1$	Not applicable when $type = 4$ (sealed) or $type = 5$ (sealed-return). The end memory address of the memory region associated with the capability

Name	Range	Description
perms	0..4	Not applicable when <code>type = 4</code> (sealed) or <code>type = 5</code> (sealed-return). The permissions associated with the capability: 0 = no access, 1 = read-only, 2 = read-execute, 3 = read-write, 4 = read-write-execute
count	0..31	Only applicable when <code>type = 4</code> (sealed) or <code>type = 5</code> (sealed-return). The number of register values sealed in the region.
reg	0..31	Only applicable when <code>type = 5</code> (sealed-return). The index of the general-purpose register to restore the capability to.

The range of the `perms` field has a partial order $\Leftarrow$ defined as follows:

$$\Leftarrow = \{ (0, 0), (1, 1), (2, 2), (3, 3), (4, 4), (0, 1), (0, 2), (0, 3), (0, 4), (1, 2), (1, 3), (1, 4), (2, 4), (3, 4) \}$$

We say a capability `c` aliases with a capability `d` if and only if the intersection between $[c.base, c.end)$ and $[d.base, d.end)$ is non-empty.

For two revocation capabilities `c` and `d` (i.e., `c.type = d.type = 2`), we say `c <_t d` if and only if

- `c` aliases with `d`
- The creation of `c` was earlier than the creation of `d`

In addition to the above fields, an implementation also needs to maintain sufficient metadata to test the `<_t` relation. It will be clear that for any pair of revocation capabilities that alias, the order of their creations is well-defined.

Note

The `valid` field is involved in [revocation](#), where it might be changed due to a [revocation operation](#) on a different capability. A performant implementation, therefore, may prefer not to maintain the `valid` field inline with the other fields.

Implementations are free to maintain additional fields to capabilities or compress the representation of the above fields, as long as each capability fits in `CLEN` bits. It is not required to be able to represent capabilities with all combinations of field values, as long as the following conditions are satisfied:

- For load and store instructions that move a capability between a register and memory, the

value of the capability is preserved.

- The resulting capability values of any operation are not more powerful than when the same operation is performed on a Capstone-RISC-V implementation without compression. More specifically, if an execution trace is valid (i.e., without exceptions) on the compressed implementation, then it must also be valid on the uncompressed implementation. For example, a trivial yet useless compression would be to store nothing and always return a capability with `valid = 0` (TODO: double-check this claim).

2.2. Extension to General-Purpose Registers

The Capstone-RISC-V ISA extends each of the 32 general-purpose registers, so it contains either a capability or a raw `XLEN`-bit integer. The type of data contained in a register is maintained and confusion of the type is not allowed, except for `x0/c0` as discussed below. In assembly code, the type of data expected in a register operand is indicated by the alias used for the register, as summarised in the following table.

<code>XLEN</code> -bit integer	Capability
<code>x0/zero</code>	<code>c0/cnull</code>
<code>x1/ra</code>	<code>c1/cra</code>
<code>x2/sp</code>	<code>c2/csp</code>
<code>x3/gp</code>	<code>c3/cgp</code>
<code>x4/tp</code>	<code>c4/ctp</code>
<code>x5/t0</code>	<code>c5/ct0</code>
<code>x6/t1</code>	<code>c6/ct1</code>
<code>x7/t2</code>	<code>c7/ct2</code>
<code>x8/s0/fp</code>	<code>c8/cs0/cfp</code>
<code>x9/s1</code>	<code>c9/cs1</code>
<code>x10/a0</code>	<code>c10/ca0</code>
<code>x11/a1</code>	<code>c11/ca1</code>
<code>x12/a2</code>	<code>c12/ca2</code>
<code>x13/a3</code>	<code>c13/ca3</code>
<code>x14/a4</code>	<code>c14/ca4</code>
<code>x15/a5</code>	<code>c15/ca5</code>
<code>x16/a6</code>	<code>c16/ca6</code>
<code>x17/a7</code>	<code>c17/ca7</code>
<code>x18/s2</code>	<code>c18/cs2</code>
<code>x19/s3</code>	<code>c19/cs3</code>
<code>x20/s4</code>	<code>c20/cs4</code>

XLEN-bit integer	Capability
x21/s5	c21/cs5
x22/s6	c22/cs6
x23/s7	c23/cs7
x24/s8	c24/cs8
x25/s9	c25/cs9
x26/s10	c26/cs10
x27/s11	c27/cs11
x28/t3	c28/ct3
x29/t4	c29/ct4
x30/t5	c30/ct5
x31/t6	c31/ct6

`x0/c0` is a read-only register that can be used both as an integer and as a capability, depending on the context. When used as an integer, it has the value `0`. When used as a capability, it has the value `{ valid = 0, type = 0, cursor = 0, base = 0, end = 0, perms = 0 }`. Any attempt to write to `x0/c0` will be silently ignored (no exceptions are raised).

2.3. Extension to Other Registers

Similar to the general-purpose registers, the program counter (`pc`) is also extended to contain a capability or an integer.

2.4. Added Registers

The Capstone-RISC-V ISA adds the following registers:

- `ceh`: the sealed capability for the exception handler

2.5. Extension to Memory

The memory is addressed using an XLEN-bit integer at byte-level granularity. In addition to raw integers, each CLEN-bit aligned address can also store a capability. The type of data contained in a memory location is maintained and confusion of the type is not allowed.

2.6. Instruction Set

The Capstone-RISC-V instruction set is based on the RV64G instruction set. The (uncompressed) instructions are fixed 32-bit wide, and laid out in memory in little-endian order. In the encoding space of the RV64G instruction set, Capstone-RISC-V instructions occupies the "custom-2" subset, i.e., the opcode of all Capstone-RISC-V instructions is `0b1011011`.

Capstone-RISC-V instruction encodings follow two basic formats: R-type and I-type, as described

below (more details are also provided in the *RISC-V ISA Manual*).




Figure 1. R-type instruction format




Figure 2. I-type instruction format

R-type instructions receive up to three register operands, and I-type instructions receive up to two register operands and a 12-bit-wide immediate operand.

3. Capability Manipulation Instructions

Capstone provides instructions for creating, modifying, and destroying capabilities. Note that due to the guarantee of provenance of capabilities, those instructions are the *only* way to manipulate capabilities. In particular, it is not possible to manipulate capabilities by manipulating the content of a memory location or register using other instructions.

3.1. Cursor, Bounds, and Permissions Manipulation

3.1.1. Capability Movement

Capabilities can be moved between registers with the MOVC instruction.




Figure 3. MOVC instruction format

An exception is raised when any of the following conditions are met:

- **rs1** does not contain a capability

If no exception is raised: If **rs1** is the same register as **rd**, the instruction is a no-op. If **rs1** is not the same register as **rd**, **rd** will contain the original content of **rs1**, and if the content is not a non-linear capability (i.e., **type** != 1), **rs1** will be set to the content of **null**.

3.1.2. Cursor Increment

The CINCOFFSET and CINCOFFSETIMM instructions increment the **cursor** of a capability by a give amount (offset).



Figure 4. CINCOFFSET instruction format



Figure 5. CINCOFFSETIMM instruction format

An exception is raised when any of the following conditions are met:

- **rs1** does not contain a capability.
- **rs2** does not contain an integer (for CINCOFFSET).
- The capability in **rs1** has **type** = 3 (uninitialised).

If no exception is raised: For CINCOFFSET, the offset is read from **rs2**. For CINCOFFSETIMM, the offset is the 12-bit sign-extended immediate field **imm**. If the offset is 0, the instructions are semantically equivalent to **MOVC rd, rs1**. Otherwise, the instructions are equal to an atomic

execution of `MOVC rd, rs1` followed by an increment of the `cursor` field of `rd` by the offset.

3.1.3. Cursor Setter and Getter

The `cursor` field of a capability can also be directly set and read with the SCC and LCC instructions respectively.




Figure 6. SCC instruction format




Figure 7. LCC instruction format

For SCC, an exception is raised if any of the following conditions are met:

- `rd` does not contain a capability.
- `rs1` does not contain an integer.
- The capability in `rd` has `type = 3` (uninitialised), `type = 4` (sealed), or `type = 5` (sealed-return).

For LCC, an exception is raised if any of the following conditions are met:

- `rs1` does not contain a capability.
- The capability in `rs1` has `type = 4` (sealed) or `type = 5` (sealed-return).

3.1.4. Bounds Shrinking

The bounds (`base` and `end` fields) of a capability can be shrunk with the SHRINK instruction.




Figure 8. SHRINK instruction format

The instruction reads `rs1` and `rs2` and attempts to set the bounds of the capability in `rd` to [`rs1`, `rs2`).

An exception is raised when any of the following conditions are met:

- `rd` does not contain a capability.
- The `type` field of the capability in `rd` is not `0`, `1`, or `3` (linear, non-linear, or uninitialised).
- `rs1` does not contain an integer.
- `rs2` does not contain an integer.
- `rs1 > rs2`.
- The original bounds of the capability in `rd` are [`base`, `end`) and `rs1 < base` or `rs2 > end`.

3.1.5. Bounds Splitting

The SPLIT instruction can split a capability into two by splitting the bounds.




Figure 9. SPLIT instruction format

The instruction reads a capability from `rs1` and an integer from `rs2` and attempts to split the capability into two capabilities, one with bounds `[base, rs2)` and the other with bounds `[rs2, end)`, assuming the original bounds were `[base, end)`.

An exception is raised when any of the following conditions are met:

- `rs1` does not contain a capability.
- `rs2` does not contain an integer.
- The `type` field of the capability in `rs1` is neither `0` nor `1` (neither linear nor non-linear).
- The original bounds of the capability in `rs1` are `[base, end)` and `rs2 < base` or `rs2 > end`.

If no exception is raised: The capability in `rs1` has its `end` field set to `rs2`. A new capability is created with `base = rs2` and the other fields equal to those of the original capability in `rs1`. The new capability is written to `rd`.

3.1.6. Permission Tightening

The TIGHTEN instruction tightens the permissions (`perms` field) of a capability.




Figure 10. TIGHTEN instruction format

The instruction reads the new permissions from `rs1` and attempts to set the `perms` field of the capability in `rd` to `rs1`.

An exception is raised when any of the following conditions are met:

- `rd` does not contain a capability.
- The `type` field of the capability in `rd` is not `0`, `1`, or `3` (linear, non-linear, or uninitialised).
- `rs1` does not contain an integer.
- The content of `rs1` is outside the range of `perms`.
- The `perms` field of the capability in `rd` is `p` and `rs1 <= p` does not hold.

3.2. Type Manipulation

Some instructions affect the `type` field of a capability.

3.2.1. Delinearisation

The DELIN instruction delinearises a linear capability.




Figure 11. DELIN instruction format

An exception is raised when any of the following conditions are met:

- **rd** does not contain a capability.
- The **type** field of the capability in **rd** is not 0 (linear).

If no exception is raised: The **type** field of the capability in **rd** is set to 1 (non-linear).

3.2.2. Initialisation

The INIT instruction transforms an uninitialised capability into a linear capability after its associated memory region has been fully initialised (written with new data).




Figure 12. INIT instruction format

An exception is raised when any of the following conditions are met:

- **rd** does not contain a capability.
- The **type** field of the capability in **rd** is not 3 (uninitialised).
- The **end** field and the **cursor** field of the capability in **rd** are not equal.

If no exception is raised: The **type** field of the capability in **rd** is set to 0 (linear).

3.2.3. Sealing

The SEAL instruction seals a linear capability.




Figure 13. SEAL instruction format

An exception is raised when any of the following conditions are met:

- **rd** does not contain a capability.
- The **type** field of the capability in **rd** is not 0 (linear).
- The **perms** field of the capability in **rd** is not 3 (read-write) or 4 (read-write-execute).
- The size of the memory region associated with the capability in **rd** is smaller than $CLEN * 32$. That is, $end - base < CLEN * 32$.

- `rs1` does not contain an integer.
- The integer contained in `rs1` is not larger than 31.

If no exception is raised: The `type` field of the capability in `rd` is set to 2 (sealed). The `count` field set to the integer contained in `rs1`.

3.3. Dropping

TODO: check whether dropping is actually necessary.

The DROP instruction invalidates a capability.




Figure 14. DROP instruction format

An exception is raised when any of the following conditions are met:

- `rs1` does not contain a capability.

If no exception is raised: The `valid` field of the capability in `rs1` is set to 0 (invalid).

3.4. Revocation

3.4.1. Revocation Capability Creation

The MREV instruction creates a revocation capability.




Figure 15. MREV instruction format

An exception is raised when any of the following conditions are met:

- `rs1` does not contain a capability.
- The `type` field of the capability in `rs1` is not 0 (linear).
- The `valid` field of the capability in `rs1` is 0 (invalid).

If no exception is raised: A new capability is created in `rd` with the same `base`, `end`, `perms`, `cursor`, and `offset` fields as the capability in `rs1`. The `type` field of the new capability is set to 2 (revocation).

3.4.2. Revocation Operation

The REVOKE instruction revokes a capability.




Figure 16. REVOKE instruction format

An exception is raised when any of the following conditions are met:

- `rs1` does not contain a capability.
- The `type` field of the capability in `rs1` is not `2` (revocation).
- The `valid` field of the capability in `rs1` is `0` (invalid).

If no exception is raised: For all capabilities `c` in the system (in either a register or memory location), its `valid` field is set to `0` (invalid) if any of the following conditions are met:

- The `type` field of `c` is not `2` (revocation), the `valid` field of `c` is `1` (valid), and `c` aliases with `rs1`
- The `type` field of `c` is `2` (revocation), the `valid` field of `c` is `1` (valid), and `rs1 < t c`

If any `c` that is not a non-linear capability (i.e., `c.type != 1`) is invalidated, then the `type` field of `rs1` is set to `3` (uninitialised), and its `cursor` field is set to `base`. Otherwise, the `type` field of `rs1` is set to `0` (linear).

4. Memory Access Instructions

4.1. Load/Store with Capabilities

4.2. Load/Store Capabilities

5. Control Flow Instructions

5.1. Jump to Capabilities

The JMP and JNZ instructions allow jumping to a capability, i.e., setting the program counter to a given capability.




Figure 17. JMP instruction format




Figure 18. JNZ instruction format

An exception is raised when any of the following conditions are met:

- **rs1** does not contain a capability.

If no exception is raised: For JMP instruction, the program counter (**pc**) is set to the capability in **rs1**. If the capability is valid and executable, the next instruction will be fetched from its **cursor** field.

The behaviour of JNZ depends on the content of **rs2**:

- If the content of **rs2** is zero (**0**), the behaviour is the same as for NOP.
- Otherwise, the behaviour is the same as for JMP.

5.2. Domain Crossing

Domains in Capstone-RISC-V are individual software compartments that are protected by a safe context switching mechanism, i.e., domain crossing. The mechanism is provided by the CALL and RETURN instructions.




Figure 19. CALL instruction format




Figure 20. RETURN instruction format

An exception is raised when any of the following conditions are met:

- **rs1** does not contain a capability.
- The **valid** field of the capability in **rs1** is **0** (invalid).

- The **type** field of the capability in **rs1** is not 4 (sealed).

For RETURN, an exception is raised also when any of the following conditions are met:

- **rs2** does not contain an integer

If no exception is raised:

For CALL:

1. Load the content at the memory location $[base, base + CLEN]$, where **base** is the **base** field of the capability in **rs1**, to the program counter (**pc**).
2. For $i = 1, 2, \dots, count$, load the content at the memory location $[base + i * CLEN, base + (i + 1) * CLEN]$, where **count** is the **count** field of the capability in **rs1**, to $x[i]$ (the i -th general-purpose register).
3. Store the old **pc** value to the memory location $[base, base + CLEN]$, and the old **sp** value to the memory location $[base + CLEN, base + 2 * CLEN]$.
4. Set the **type** field of the capability in **rs1** to 5 (sealed-return), and write the capability to the register **cra**.

For RETURN when the content of **rs1** is 0:

1. Load the content at the memory location $[base, base + CLEN]$, where **base** is the **base** field of the capability in **cra**, to the program counter (**pc**).
2. For $i = 1, 2, \dots, 31$, load the content at the memory location $[base + i * CLEN, base + (i + 1) * CLEN]$, to $x[i]$ (the i -th general-purpose register).
3. Write the old **pc** value with the **cursor** field replaced with the content of **rs2** to the memory location $[base, base + CLEN]$.
4. For $i = 1, 2, \dots, count$, store the content of $x[i]$ (the i -th general-purpose register) to the memory location $[base + i * CLEN, base + (i + 1) * CLEN]$, where **count** is the **count** field of the capability in **rs1**.
5. Set the **type** field of the capability in **cra** to 4 (sealed), and write the capability to the exception handler register **ceh**.

For RETURN when the content of **rs1** is not 0:

1. Load the content at the memory location $[base, base + CLEN]$, where **base** is the **base** field of the capability in **rs1**, to the program counter (**pc**).
2. Load the content at the memory location $[base + CLEN, base + 2 * CLEN]$, where **base** is the **base** field of the capability in **rs1**, to the stack pointer (**sp**).
3. Write the old **pc** value with the **cursor** field replaced with the content of **rs2** to the memory location $[base, base + CLEN]$.
4. For $i = 1, 2, \dots, count$, store the content of $x[i]$ (the i -th general-purpose register) to the memory location $[base + i * CLEN, base + (i + 1) * CLEN]$, where **count** is the **count** field of the capability in **rs1**.
5. Set the **type** field of the capability in **rs1** to 4 (sealed), and write the capability to the register

$X[\text{reg}]$ where reg is the reg field of the capability in rs1 .

5.3. World Switching

TransCapstone-RISC-V is an extended version of Capstone-RISC-V which adds a pair of extra instructions CAPENTER and CAPEXIT to support switching between the secure world and the normal world.




Figure 21. CAPENTER instruction format




Figure 22. CAPEXIT instruction format

6. Adjustments to Existing Instructions

TODO

7. Interrupts and Exceptions

TODO

8. Memory Consistency Model

TODO

Appendix A: Debugging Instructions (Non-Normative)

TODO

Appendix B: Instruction Listing




Figure 23. Instruction format: R-type




Figure 24. Instruction format: I-type

Table 2. Debugging instructions

Mnemonic	Format	Func3	Func7	rs1	rs2	rd	imm[11:0]
QUERY	R	000	0000000	I	-	-	-
RCUPDATE	R	000	0000001	I	-	I	-
ALLOC	R	000	0000010	I	-	I	-
REV	R	000	0000011	I	-	-	-
CAPCREATE	R	000	0000100	-	-	C	-
CAPTYPE	R	000	0000101	I	-	C	-
CAPNODE	R	000	0000110	I	-	C	-
CAPPERM	R	000	0000111	I	-	C	-
CAPBOUND	R	000	0001000	I	I	C	-
CAPPRINT	R	000	0001001	I	-	-	-
TAGSET	R	000	0001010	I	I	-	-
TAGGET	R	000	0001011	I	-	I	-

Table 3. Capability manipulation instructions

Mnemonic	Format	Func3	Func7	rs1	rs2	rd	imm[11:0]
REVOKE	R	001	0000000	C	-	-	-
SHRINK	R	001	0000001	I	I	C	-
TIGHTEN	R	001	0000010	I	-	C	-
DELIN	R	001	0000011	-	-	C	-
LCC	R	001	0000100	C	-	I	-
SCC	R	001	0000101	I	-	C	-
SPLIT	R	001	0000110	C	I	C	-
SEAL	R	001	0000111	I	-	C	-
MREV	R	001	0001000	C	-	C	-
INIT	R	001	0001001	-	-	C	-

Mnemonic	Format	Func3	Func7	rs1	rs2	rd	imm[11:0]
MOVC	R	001	0001010	C	-	C	-
DROP	R	001	0001011	C	-	-	-
CAPGET	R	001	0001100	-	-	C	-
CINCOFFSET	R	001	0001101	C	I	C	-
CINCOFFSETIMM	I	011	-	C	-	C	S

Table 4. Memory access instructions

Mnemonic	Format	Func3	Func7	rs1	rs2	rd	imm[11:0]
LDC	R	001	0010000	C	-	C	-
STC	R	001	0010001	C	C	-	-
LDD	R	001	0010010	C	-	I	-
STD	R	001	0010011	C	I	-	-
LDW	R	001	0010100	C	-	I	-
STW	R	001	0010101	C	I	-	-
LDH	R	001	0010110	C	-	I	-
STH	R	001	0010111	C	I	-	-
LDB	R	001	0011000	C	-	I	-
STB	R	001	0011001	C	I	-	-

Table 5. Control flow instructions

Mnemonic	Format	Func3	Func7	rs1	rs2	rd	imm[11:0]
CALL	R	001	0100000	C	-	-	-
RETURN	R	001	0100001	C	I	-	-
JMP	R	001	0100010	C	-	-	-
JNZ	R	001	0100011	C	I	-	-
CAPENTER	R	001	0100100	C	-	-	-
CAPEXIT	R	001	0100101	C	I	-	-

Note

For instruction operands:

I

Integer register

C

Capability register

-
Not used

For immediates:

S
Sign-extended

Z
Zero-extended

-
Not used

Appendix C: Assembly Code Examples

TODO

Appendix D: Abstract Binary Interface (Non-Normative)

TODO